



* See MP Systems Hardware Guide available via the “Help” menu in *AcqKnowledge*. The guide contains a table describing the meaning of different LED patterns for the Activity and Busy LEDs. Under normal operation when not acquiring data, Busy LED is off, and Activity LED flashes (amber) at irregular intervals. If Activity LED double flashes at regular intervals (newer MP150s) or if Activity and Busy LEDs flash alternately (older MP150s), then MP150 does not detect that it is connected to a network.